

4IN1 DVB-C SD Encoder Modulator



Overview

SD Encoder Modulator supports 4×CVBS and 4 pairs of unbalanced audio input and 1×RF output. After coded and modulated, the input signal can be directly output or mixed output with original TV signal. It can be widely used in home entertainment, security and protection monitoring, hotel LCD panels, shopping mall advertising and other similar places.

Feature

- Integrated encoder and modulator
- 4CVBS+Audio and 1×RF input
- DVB-C RF out
- RF Range: 47-870Mhz
- Keyboard+LCD control and network management

Technical Specification

Input	Video Signal	4×CVBS, BNC interface, level 1.0 Vp-p	
	Audio Signal	4 pairs of unbalanced audio, BNC interface, level 2.0 Vp-p	
	RF (47-870MHz)	1×DVB-C RF, F-head	
Video Coding		comply with ISO11172 (MPEG-1) & ISO13818 (MPEG-2)	
		MPEG-2 coding adopt MP@ML (4:2:0)	
		MPEG-2 Adaptive Field Frame (AFF)	
		MPEG-2 Field-Based (FB)	
Resolution		720×576 (PAL); 720×480 (NTSC)	
Bit Rate		1.0~15Mbps continuously adjustable per channel	
Audio Coding	Sampling	32KHz, 44.1KHz, 48KHz	
	Code Rate	64, 96, 128, 256, 384Kbps	
	Property	MPEG-1, Layer 1/2	
Output		1×DVB-C RF (47-870MHz), F-head	
DVB-C Modulation		Frequency Range: 47~870MHz, 1KHz step	Output Level: 80-110dB
		Constellation: 16/32/64/128/256-QAM	Symbol Rate: 5-9Msps
		Error-Correcting Codes: RS code 188/204	BER: 0
		Impedance: 75Ω	MER: ≥32dB
		Level Attenuation Range: 0~30dB (0.5dB step)	
General Features	Size	482mm×410mm×44mm	
	Temperature Range	0~45°C (operation); -20~80°C (storage)	
	Power	100-240VAC, 50Hz, 25W	